

00 Subsequently in step S200, it is determined whether the country selection flag has been set in the EEPROM 118B. If the country selection flag has not been set (NO in step S200), that is, if the specification of a designated importing country has not been selected nor stored into the EEPROM 118B, the operation proceeds to step S300. In step S300, a country selecting program for selecting the specification of the importing country and storing it into the EEPROM 118B is read from the ROM 118A, so that the country selecting operation is started.

Page 27, lines 19-25, delete current paragraph and insert therefor:

03 Subsequently in step S400, the control unit 117 causes the display 106 to sequentially display the country names pre-stored in the ROM 118A together with their selection numbers for a predetermined time period for each country name in repeated cycles (about 1 second for each country name at a time in this embodiment). That is, the display 106 displays the country names in the order of, for example, "1: BELGIUM", "2: ITALY", "3: SWEDEN", "1: BELGIUM", ..., where the selection numbers for Belgium, Italy and Sweden are "1", "2" and "3", respectively.

Page 27, line 26 - Page 28, line 3, delete current paragraph and insert therefor:

04 Subsequently in step S500, if an operating person at the adjustment line presses a numerical key of the dial keys 111 corresponding to the selection number of the designated importing country, the control unit 117 reads the specification of the country corresponding to the input selection number from the ROM 118A, and stores the specification into the EEPROM 118B.

Page 28, lines 4-10, delete current paragraph and insert therefor:

05 Subsequently in step S600, the control unit 117 causes the display 106 to display the country name corresponding to the input selection number together with the selection number for a predetermined time, such as about 10 seconds, to inquire of the operating person at the adjustment

05 line whether the operating person needs to correct the selection. For example, if the numerical key "2" has been pressed, the display 106 displays "2: Italy ?". Therefore, in step S600, the control unit 117 can determine whether country selection has been completed.

Page 28, lines 11-15, delete current paragraph and insert therefor:

06 If any one of the numerical keys corresponding to the other selection numbers is pressed within the predetermined time following the start of display of the selection number and the country name inputted by the operating person, the control unit 117 determines that a new selection number has been inputted (NO in step S600). In this case, the control unit 117 returns to step S500.

Page 28, lines 16-22, delete current paragraph and insert therefor:

07 Conversely, if none of the numerical keys corresponding to the other selection numbers is pressed within the predetermined time following the start of display of the selection number and the country name, the control unit 117 determines that the specification corresponding to the designated importing country has been selected (YES in step S600). Subsequently, the control unit 117 reads the country selection flag from the EEPROM 118B, and sets the flag, and then stores it back into the EEPROM 118B. Then, the operation returns to step S200.

Page 28, lines 23-26, delete current paragraph and insert therefor:

08 If it is determined in step S200 that the country selection flag has been set in the EEPROM 118B (YES in step S200), the operation goes to step S700, in which the control unit 117 reads the main program from the ROM 118A, and starts executing the main program.

Page 28, line 27 - Page 29, line 3, delete current paragraph and insert therefor:

09 Subsequently in step S800, the main program is operated on the basis of the specification of the selected country stored in the EEPROM 118B (for example, the specification of Italy). That is, the facsimile apparatus 101 now operates on the basis of the specification of the designated importing country.